2D Desktop Barcode Scanner User Manual

3 1 9 0 0 5 0 4 3 0

V:2510

Switch On/Off Setting Codes

Scan "Switch on Setting Codes" to activate the Setting Codes function;
If need to exit the setting code function, please scan the " switch off setting code", or scan a normal barcode other than the setting code

Switch On Setting Codes

Switch Off Setting Codes (default)

Restore Factory Default Setting

Scan below QR setting code, the scanner will be restored to factory default setting.

Restore Factory Default Setting

Default Configuration: Interface USB
Operating way: Auto Trigger
Ending character: Enter

Interface Configuration

USB Interface

When you want to connect the scanner with devices by USB cable, you could scan below QR code to configure the scanner for standard keyboard mode

*USB

USB COM(Virtual COM)

When you want to connect the scanner with devices by USB cable, you could scan below QR code to configure the scanner for virtual COM output mode(It will need driver, please contact your supplier to make the driver installation)

Virtual COM

COM(RS-232)

When you want to connect the scanner with device by RS-232 interface, you need to match the same configuration between the scanner and device, default COM interface configuration: 9600 Baud rate, 8 bit data, No check bit, 1 stop bit.

RS-232

Sound Volume

On

Off

Low

Medium

High(Default)

Language Settings

(*)English (US)

English (UK)

French (France)

Italian (Italy)

German (Germany)

Spanish (Spain)

Russian

Portuguese

Portuguese - Brazil

Thai

Vietnam

Latin American

Virtual Keyboard Setting

Under Virtual keyboard circumstance, the device could output correct information even by any language keyboard mode. When use virtual keyboard, please be sure the small numbers keyboard is working(Default is standard)

*Standard Keyboard

Virtual Keyboard

Bar Code Types Reading Ability Configuration

Scan below QR code to allow or forbid reading certain type of barcode. But in this situation (Read all 1D/2D barcode), the speed of decoding may slow down. It is better to choose the code types that you need to improve the decoding speed

Read all 1D Barcode

Disallow reading 1D barcode

Read all 2D Barcode

Disallow reading 2D barcode

1D Reading Reverse Image Barcode

Allow

*Forbidden

2D Reading Reverse Image Barcode

Allow

*Forbidden

Suffix Configuration

User could configure the suffix by below setting codes

No Suffix

*CR

CR+LF

TAB

Environmental Tips

Environment-friendly use period of this product is 10 years. Climatic conditions for normal work, storage, and transportation specified in the technical characteristics of the product.

Assembly unit name	Harmful substances					
	Pb	Hg	Cd	Cr(VI)	PBB	PBDE
Shell	○	○	○	○	○	○
PCB	×	○	○	○	○	○
Cable	○	○	○	○	○	○
Packaging Materials	○	○	○	○	○	○

This form is prepared according to the provisions of SJ/T 11364.

○ : It is indicated that the content of the harmful substance in all the homogeneous materials of the component is below the limit specified in GB/T 26572.

× : It is indicated that the content of the harmful substance at least in one certain homogeneous material of the component is beyond the limit specified in GB/T 26572.

Note: 1. Most components in this product use harmless environment-friendly materials, and due to limited international technology level, some harmful materials cannot be replaced.
2. The environmental data for reference are tested in the normal use and storage environment of this product requirements, such as humidity and temperature, etc.

Warranty Card

1. Customers can enjoy the legal rights using the purchase invoice and the warranty card without doing any warranty procedures.
2. All the warranty items are subject to the guarantee clause and user notice that published by our company.
3. We will not guarantee the product if it is in one of the following situation, but we can offer maintenance service with charges.
   (1) Man-made damage or improper operation;
   (2) Damage caused by maintenance of non-professionals;
   (3) Have no warranty card,the model is inconsistent with actual or the warranty card is obliterated;
   (4) Irresistible damage (natural disasters like thunder, earthquake, fire, etc).
4. Please fill in the warranty card.Do no obliteate the card. Otherwise,we will make charges maintenance.
5. Please keep this card well. We will not offer another warranty card.

Barcode Scanner Warranty Proof

User Name		Telephone	
Address			
Purchasing Date	D/ M/ Y	Model	
Serial NO.		Agency	
Maintenance Record			
Date	Product Failure	Maintenance Condition	Repairman